

IVR 16CH H.264



IVR

IVR-1681E-B

MAIN FEATURES

- ☐ Support 1080P Realtime Recording
- ☐ 18 Ports (16x Port PoE Camera, 1 internet 1 Lan)
- ☐ Built-in 16 Port switch for camera, with PoE Function
- ☐ Support Max 3 Sata
- ☐ P2P Remote access support
- ☐ Web-Base Management
- ☐ iCMS Systems Support
- ☐ HDMI+VGA output Max 1920x1080

IVR

Order information

IVR-1681E-B



Dimension(mm) : 442(w)x92(h)x300(d)

Net.W: 7.73 kgws Gross. W: 8.33 kgws

Model		IVR-1681E-B
Video	Input	16CH (8CH 1080P (PoE), 8CH through LAN)
	Output	Max. 3840 x 2160 1 HDMI with Audio and 1 VGA
Audio	Output	1
System	Operating System	Embedded Linux OS
	SATA Devices	Supports Max. x 7 SATA Devices (HDDx6+eSATAx1,HDDx4+Optical Devicex1+eSATAx1)
	External HDD	YES (eSATA)
	Alarm In /Relay Out	Alarm-in x 8 Relay-out x 4
	Serial Interface	RS-485 *2
	USB 2.0 Ports	USB 2.0 x2 , USB 3.0 x1
	Dimension (mm)	442(w)x92(h)x438(d)
	Power Rating	AC 110/220V 300W With 48V (PoE)
Display	Split Screen	1, 4, 9, 13, 16, SEQ.
	Auto Channel Switching	Switching time : 1 ~ 99 sec
	Mode	Zoom, PIP, Auto SEQ.
Recording	Recording Throughput	1280 * 720 @ 30/25 fps
	(60Hz /50Hz IP Camera)	1920 * 1080 @ 30/25 fps
	Mode	Continuous, Event, Schedule
Playback	Search Mode	Date/time, Event
	Zoom	*Digital (x2 ~ x5)
Network	Network Interface	10/100/1000 Ethernet
	Protocol	TCP/IP, SMTP, HTTP, DHCP, PPPoE(ADSL), NTP, DDNS, FTP, SMTP
	Onvif	YES
	Remote Software	iWatch DVR, IE Browser, iCMS
	Account	1 Admin + 10 Users
	Mobile Device	Windows Phone, iPhone, iPad, Android
Backup	Interface	USB 2.0
	Audio Backup	YES
	Backup Type	Network, Ext. USB flash device , SATA optical DVD..etc
Alarm	Event Log	Up to the 10000 events
		(Sensor, Motion, video Loss, power on, remote login, logout, HDD error, HDD full)

IVR

Model		IVR 860E-J
OSD & DVR Control	Multi-Language	Supported
	Touch Panel	Touch Panel LCD Monitor
		(USB Interface, EETI Chipset Only)
	System Upgrade	USB Flash Drive, iWatch DVR